



WAYFARER™ WFA120KU

1.2m Ku-Band Auto Fly-Away

The Norsat WAYFARER™ commercial 1.2m fly-away antenna is a fast deploying, easy-to-use, and compact SATCOM VSAT. This antenna is an excellent choice for commercial applications in various industries.

The WAYFARER 1.2m fly-away antenna offers excellent rugged and reliable satellite links for remote enterprise, energy, emergency, and media applications.

FEATURES

- Easy and intuitive LinkControl™ Interface
- Rugged and lightweight pedestal design
- Lightweight and durable 8 segment carbon fiber reflector
- Fast, simple, tool-free deployment
- Automatic 3-axis acquisition
- 2-case packing solution
- Wide range of Norsat BUC and LNB configurations
- Set up in 5 minutes



SPECIFICATIONS

ELECTRICAL

Reflector aperture	1.2m
Reflector material	Carbon fiber
Feed configuration	Center
Tx frequency	13.75 to 14.50 GHz
Rx frequency	10.70 to 12.75 GHz
Tx gain	42.8 + 20log (f/14.125) dBi
Rx gain	41.5 dBi + 20log (f/11.85) dBi
Polarization	Linear
Cross polarization (On-Axis)	≥35 dB
Tx/Rx isolation (port isolation)	Tx: ≥ 85 dB; Rx: ≥ 40 dB
Sidelobe	First sidelobe -14 dB
Azimuth range	± 200°
Elevation range	10° to 90°
Polarization range	± 90°
Azimuth speed	0.1°/s to 3°/s
Elevation speed	0.1°/s to 3°/s
Polarization speed	0.1°/s to 1°/s
Feed interface	WR75
Power supply	AC110-230V 50/60Hz, rated 200W, 550W max

MECHANICAL

Ruggedized weatherproof case		
Case 1	Pedestal assembly	Size: 84.5 cm (L) x 62 cm (W) x 49 cm (H); Weight: ≤30Kg
Case 2	Reflector / feed	Size: 84.5 cm (L) x 62 cm (W) x 49 cm (H); Weight: ≤22Kg

ENVIRONMENTAL

Wind load - operational	36 km/h
Wind load - survival	61 km/h
Temperature	-30°C to +60°C
Humidity	0-95%
Water ingress	IP 65 (antenna only)

WAYFARER WFA120KU 1.2M KU-BAND AUTO FLY-AWAY ANTENNA

HOW TO ORDER

WFA120KU-NA

AC POWER PLUG

NA = North America (NEMA 5/15)

UK = UK (BS 1363)

EU = Europe (CEE 7/7)

IEC = IEC (60320 CIA)

ACCESSORY OPTIONS

BUC OPTIONS

2W

ELMTBKU002

Via IFL Cable Connection

Not Applicable

Not Required

3W

ELMTBKU003

Via IFL Cable Connection

Not Applicable

Not Required

4W

ELMTBKU004

Via IFL Cable Connection

Not Applicable

Not Required

6W

ELMTBKU006

Via IFL Cable Connection

Not Applicable

WFA120KUMT-006

8W

ELMTBKU008

Via IFL Cable Connection

Not Applicable

WFA120KUMT-008

10W

ELMTBKU010

Via IFL Cable Connection

Not Applicable

WFA120KUMT-010

16W

ATOMBKU016

PS300-AT1(NA/UK/EU/IEC)

CABLEM+C-AT10

WFA120KUMT-024

20W

ATOMBKU020

PS300-AT1(NA/UK/EU/IEC)

CABLEM+C-AT10

WFA120KUMT-024

40W

ATOMBKU040

PS300-AT1(NA/UK/EU/IEC)

CABLEM+C-AT10

WFA120KUMT-024

BUC OPTIONS	BUC	BUC POWER SUPPLY	BUC M & C CABLE	BUC MOUNTING BRACKETS
2W	ELMTBKU002	Via IFL Cable Connection	Not Applicable	Not Required
3W	ELMTBKU003	Via IFL Cable Connection	Not Applicable	Not Required
4W	ELMTBKU004	Via IFL Cable Connection	Not Applicable	Not Required
6W	ELMTBKU006	Via IFL Cable Connection	Not Applicable	WFA120KUMT-006
8W	ELMTBKU008	Via IFL Cable Connection	Not Applicable	WFA120KUMT-008
10W	ELMTBKU010	Via IFL Cable Connection	Not Applicable	WFA120KUMT-010
16W	ATOMBKU016	PS300-AT1(NA/UK/EU/IEC)	CABLEM+C-AT10	WFA120KUMT-024
20W	ATOMBKU020	PS300-AT1(NA/UK/EU/IEC)	CABLEM+C-AT10	WFA120KUMT-024
40W	ATOMBKU040	PS300-AT1(NA/UK/EU/IEC)	CABLEM+C-AT10	WFA120KUMT-024

LNB OPTIONS

LNB 1000H or HS1000 Series, with Type F (75 Ohm) Connector

IFL CABLE OPTIONS

IFL Cable (10m)

NN-FF

IFL-NN-FF-10

NN-NN

IFL-NN-NN-10

FN-NN

IFL-FN-NN-10

FN-FF

IFL-FN-FF-10

MODEM CABLE OPTION (For iDirect product only)

MOD-CABLE

INTEGRATION

WF-INT Assembly, function verification, and pointing test (standard product/RF packages only)

Custom integration also available. Contact sales@norsat.com for more information.